



CBKLEDS-HVG-BLK

Bunkalite IP65 Weatherproof Circular Emergency, CLP, Sustained, Zoneworks XT Hive, Black



PRODUCT INFORMATION					
Part Number	CBKLEDS-HVG-BLK				
MIC	UKS02820040002				
Description	Bunkalite IP65 Weatherproof Circular Emergency, CLP, Sustained, Zoneworks XT Hive, Black				
Construction	Base Material: Die-cast aluminium Diffuser Cover Material: Opal Polycarbonate				
Mounting	Surface Mount				
Dimensions L x W x H	360mm (Diameter), 145mm (Height)				
Weight	4.5kg				
Operating Mode	Sustained (Combined Non-Maintained)				
Testing System	Zoneworks XT HIVE (RF)				
Battery Type & Manufacturer	Lithium Iron Phosphate, Clevertronics				
Charging Method	Intelligent Current Limited Constant Voltage				
Diffuser	Constant current, 500mA, 50,000hrs				
Lamp(s)	LED module, 4,000K natural white, 50,000h life (L70/B50), Ra>80				
Operating Voltage	240V AC; 50Hz				
Supply Current	0.071A				
Power Factor	0.93				
Inrush Current (Max)	10.2A				
Earth Leakage	0.145mA				
Total Lumen Output	260lm (Emergency) 1435lm (240V/Maintained Mode)				
Power Consumption	1.2 Watts (Standby), 21 Watts (Max)				
Operating temperature	0°C to 40°C				
Rated Emergency Duration	180 minutes				
IP Rating	IP65				
IK Rating	IK10				
Protection	<ul style="list-style-type: none">• Battery overvoltage & overcurrent protection• Battery deep discharge protection• Supply voltage polarity reversal protection• Battery short-circuit protection (charging will resume upon removal of fault)• Kit box (enclosure) of lamp control gear provides protection against accidental contacts with live parts				
Luminaire Classification	<table border="1"><tr><td>X</td><td>2</td><td>ADF</td><td>180</td></tr></table>	X	2	ADF	180
X	2	ADF	180		
Conformity	BS EN 60598.2.22, BS 5266				
Compliance Marking					

*Due to changes in industry standards and Clevertronics policy of product improvement, specification details are subject to change without notice



CBKLEDS-HVG-BLK

Bunkalite IP65 Weatherproof Circular Emergency, CLP, Sustained,
Zoneworks XT Hive, Black

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1553230	Battery
UKM02870060002	Emergency Driver
1331101-B	240V Driver
8011801	LED Strip
8003250	Node

*Due to changes in industry standards and Clevertronics policy of product improvement, specification details are subject to change without notice