

After Power ON, the Status LED on a Clevertest Plus enabled fitting will display a rapid Green or Red flashing for a period up to 2 minutes.

### Zoneworks and DATA Monitored Options

Luminaires with part numbers having -ZW, -DATA are fitted with Zoneworks communications modules (nodes). These fittings are monitored using either Powerline Carrier Technology that utilises the power cable to provide data communication or a dedicated data cable to/from data routers installed on a dedicated data trunk connected to a central Server (can also be connected via Ethernet/Internet/Fibre). Zoneworks software on the server is used to monitor, coordinate testing and collate test data from each fitting and can be commissioned by scanning of the supplied barcode. The LED Test Switch indicator provides a multifunction indication of the status of the fitting during testing and normal operation:

| State                            | LED Operation                                  |
|----------------------------------|--|
| Commissioned                     | LED on Solid (Green)                           |
| Un-commissioned                  | LED flashes at 0.5Hz (0.5s Green, 0.5s Yellow) |
| Emergency Light Test In Progress | LED flashes at 3s On (Yellow) & 0.5s Off       |

In the case of the DATA version a 2-way "figure 8" cable and terminal block facilitates the connection to the DATA network via a multi-drop bus (daisy chain connection). For further information of installation of a Zoneworks system, please refer to the Zoneworks Users Guide and Commissioning Guide (incl. DATA version)

### DALI EM Option

Luminaires with part numbers CWP2LIFE-PRO-WPP0D-DALI are fitted with DALI modules (nodes) that facilitate connection and integration to 3<sup>rd</sup> Party Lighting Control Systems. Before installing the CWP2LIFE-PRO-WPP0D-DALI please confirm that the Lighting Control System has the capability to monitor DALI Emergency Luminaires. The CWP2LIFE-PRO-WPP0D-DALI will be addressed and configured into the control system by the Lighting Control System Commissioning Technicians and not Clevertronics.

| State                            | LED Operation                                   |
|----------------------------------|---|
| Commissioned/ Un-commissioned    | LED on Solid (Green)                            |
| Emergency Light Test in progress | LED flashes at 1s On (Yellow) & 1s Off          |
| "IDENTIFY COMMAND"               | Fitting goes into emergency mode for 10 seconds |

A 2-way "figure 8" cable and terminal block facilitates the connection to the DALI network OR a 5/6way "structured wiring system" lead and plug facilitating the power and DALI connection. DALI connections are marked as Da Da.

### Caution:

On many building sites, power circuits may be cut off in an uncontrolled and repetitive basis during construction. As a result, any Exit & Emergency Units, on these circuits, will have their batteries discharged or "cycled". The battery in this fitting has been selected to give excellent long-life performance in a controlled AS2293 testing environment. Excessive battery cycling will reduce through-life performance and may lead to premature battery failure. Battery warranty claims, as a result of such abuse, are specifically EXCLUDED from Clevertronics warranty terms.

### Warranty:


For Product Warranty information and Terms and Conditions of Sales please refer to our website <http://clevertronics.com.au/terms-conditions-sale-australia-nz/>

## CWP2LIFE-PRO-WPP0D

### Surface Mount Twin Head Emergency

### Installation & Maintenance Instruction Leaflet




**Designed in Australia to comply with the requirements of AS2293.3:2005 and AS/NZS CISPR15: 2011**  
NOTE: Standard product codes with this symbol  are enabled with Clevertest Plus capability. Please refer to the operation guide supplied with the product for details.

### Models: CWP2LIFE-PRO-WPP0D

#### Testing:

Manual Test xx = Blank  
Zoneworks xx = ZW  
Z/W DATA xx = DATA  
DALI Comp. xx = DALI  
Clevertest xx = CT

(NOTE: -CT Products supplied with the Clevertest Plus Symbol  are activated with Clevertest PLUS capability. Please refer to the operation guide supplied with the product for details).

### Spare Parts:

1550050 Battery, 3.2 Volt 3.2Ah Li-ion  
2750353 LP WP POD, Gen2, 2 LED, Sub Assy  
CLIFE-PRO-CKIT-NP Lifelight Pro, Control

### Important:

It is illegal for anyone, except for a licensed electrician to install or maintain this product. Before installation, ensure that the electricity supply has been switched off and isolated. Installation must be carried out in accordance with the relevant Australian and International Standards.

#### Victoria (Head Office & Manufacturing)

195 Chesterville Rd  
Moorabbin VIC 3189  
Phone: +61 3 9559 2700  
Fax: +61 3 9559 2799

#### New South Wales

Phone: +61 2 8805 6400  
Fax: +61 2 8805 6444

#### Queensland

Phone: +61 7 3442 9700  
Fax: +61 7 3442 9777

#### South Australia/Northern Territory

Phone: +61 8 8301 8800  
Fax: +61 8 8351 8286

#### Western Australia

Phone: +61 8 9248 3720  
Fax: +61 8 9248 3725

#### New Zealand

Phone: +64 800 548 448

## Installation:


This CWP2LIFE-PRO-WPPOD Surface mount non-maintained Emergency Luminaire can be installed on solid or T-BAR ceilings or used to replace an existing unit.

- Locate the installation position.
- Pre-drill mounting holes per diagram below.
- Removed fitting cover.
- Use suitable fixings to fasten the fitting to the mounting surface.
- Taking note of the terminal block position, drill a hole in the fitting box to suit the cable gland or conduit to be used for power entry.
- Terminate the supply cables to the L, N & E terminals (in the case of the –DALI or –DATA fittings terminate the DALI or DATA cable to the terminals marked Da Da or DATA).
- Ensure the Batteries and POD cables are connected.
- Screw the cover to the base.
- If the CTP capabilities are activated, please affix the CTP status Label to a visible surface.

## Networking:

When installing the product on a monitored network, (ZONWORKS, DATA, DALI) simply insert the relevant Smart Node PCA.

## Images and Dimensions:



## Initial Testing:

When the CWP2LIFE-PRO-WPPOD unit is connected to the un-switched active, it must be allowed to charge the battery for at least 24 hours. The emergency lamp only illuminates during a power failure. Conduct the following tests:

- During the first commissioning test the emergency lamp must illuminate for at least 2 hours after disconnection from the main supply. The results of all tests are required to be recorded in a service logbook, which is to be kept on-site at all times. If the unit fails to illuminate for the requisite time, remedial action must be taken to repair the situation and once completed, the unit must pass a subsequent test.
- Press and hold Test Button in each POD or switch Off Mains Supply, check that the emergency lamp is On.
- Release the Test Button or Switch on Mains Supply, check that the emergency lamp is Off (Non-maintained operation).
- Subsequent tests require the unit to illuminate for at least 90 minutes. The results of all tests are required to be recorded in a service logbook, which is to be kept on-site at all times. If the unit fails to remain illuminated for the requisite time, remedial action must be taken to repair the situation and once completed, the unit must pass a subsequent test. For more specific information, please refer to the current edition of the AS 2293.3 Standard.

## Below are a list of common problems and their possible causes:

**Fault:** The Green LED indicator is not illuminated.

**Check:** A.C. is connected and is turned on.  
Battery is connected.  
Test Switch for damage.

**Fault:** Lamp does not illuminate in emergency mode.

**Check:** A.C. is connected.  
Lamp is correctly inserted.  
Battery is connected

**Fault:** Lamp illuminates in emergency mode, but only stays on for a short period.

**Check:** Battery has been allowed to charge for at least 24 hours.  
Battery for damage.

## Rated Emergency Lumen Output in accordance with AS2293.1 (refer to spacing tables for installation positions):

Refer to the Technical Label for classification information.