



## ARGO-1500-SEN-LP-HVG

CLEVERTRONICS Argo 1500mm Weatherproof Emergency Batten, LP, Switchable Colour, Motion Sensor, Zoneworks Hive



PRODUCT INFORMATION	
Product Code	ARGO-1500-SEN-LP-HVG
MIC	AUB02920580001
Description	Argo 1500mm Weatherproof Emergency Batten, LP, Switchable Colour, Motion Sensor, Zoneworks Hive
Colour CCT	Switchable 3000K / 4000K (Default) / 5700K
Output Configuration	Fixed Single Output
Battery Configuration	Integral Battery
Construction	Polycarbonate Base, Polycarbonate Diffuser and Captive Stainless-Steel Clips (SS301)
Diffuser	Polycarbonate
Mounting	Surface Mount
Operating Mode	Sustained
Testing System	Zoneworks HIVE (RF) 2.4GHz
Battery	Lithium Iron Phosphate, 3.2V 6400mAh
Charging Method	Intelligent Current Limited Constant Voltage
Sensor Capability	High/Low, On/Off, Master Slave Capable - Yes
Dimensions LxWxH (mm)	1565 x 121 x 88
Weight (kg)	3.3
Driver / Ballast	LED Driver - TCI DC MAXI JOLLY SVM 65 DALI SLIM
Lamp(s)*	LED strip module, 3000K / 5700K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 168,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 84,000hr L90/B10 Ta 40°C; LM80 Report 37,000hr, Projected 37,000hr
Supply Voltage	220-240V~ 50Hz
Power Factor	0.92 @ Default
Supply Current	250mA +/- 20mA
Inrush Current (Peak/Duration)	17A / 76µs
Earth Leakage	0.367mA
Total lumen output	6244lm (109.16lm/W) @ default (refer to next page for details)
Power Consumption	54.9W @ default (refer to next page for details)
Operating Temperature	0°C to 40°C
IP Rating	IP65
Impact Rating	IK08
LED MacAdam Step (SDCM)	5
AS2293 Classification	C0=D63 C90=D40
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3
Compliance Marking	



## ARGO-1500-SEN-LP-HVG

CLEVERTRONICS Argo 1500mm Weatherproof Emergency Batten,  
LP, Switchable Colour, Motion Sensor, Zoneworks Hive

### REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1330151	240V Driver
8002851	240V LED Panel
AUM02970010001	Emergency Driver Pack
8002700	Emergency LED Panel
1550230	Battery
1190118	Microwave Motion Sensor

Power Consumption & Lumen Output	Output (1200mA)				Lumen Output
	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	
3000K	60.8W	58.5W	11.4W	0.7W	5904lm
4000K (DEFAULT)	57.2W	54.9W	11.2W	0.7W	6244lm
5700K	60.4W	58.1W	11.3W	0.7W	5631lm

\*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications, or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order