

ARGOPLUS-1200-LP-HV

CLEVERTRONICS Argonaut Plus 1200mm Weatherproof Emergency Batten, LP, Switchable Colour & Output, Zoneworks Hive



PRODUCT INFORMATION				
Product Code	ARGOPLUS-1200-LP-HV			
МІС	AUB02820640001			
Description	Argonaut Plus 1200mm Weatherproof Emergency Batten, LP, Switchable Colour & Output, Zoneworks Hive			
Colour CCT	Switchable 3000K / 4000K (Default) / 5700K			
Output Configuration	Switchable Dual Output			
Battery Configuration	Integral Battery			
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS304)			
Diffuser	Polycarbonate			
Mounting	Surface Mount			
Operating Mode	SUSTAINED			
Testing System	Zoneworks XTHIVE (RF)			
Battery	Lithium Iron Phosphate, 3.2V 6400mAh			
Charging Method	Intelligent current limited constant voltage			
Sensor Capability	n/a			
Dimensions LxWxH (mm)	1265x160x105			
Weight (kg)	2.9			
Driver / Ballast	LED Driver - 40w Stallion, SP, 650mA, with feet			
Lamp(s)*	LED strip module, 3000K / 5700K, Ra>80 L70/B50 Ta 40ºC; LM80 Report >60,000hr, Projected 157,000hr L80/B20 Ta 40ºC; LM80 Report >60,000hr, Projected 95,000hr L90/B10 Ta 40ºC; LM80 Report 43,000hr, Projected 43,000hr			
Supply Voltage	220-240V~ 50Hz			
Power Factor	0.94 @ default			
Supply Current	170mA +/-20mA			
Inrush Current (Max)	41.4A<500µs			
Earth Leakage	0.42mA			
Total lumen output	4420 lm (134 lm/W) @ default (refer to next page for details)			
Power Consumption	32.9W @ default (refer to next page for details)			
Operating Temperature	0°C to 40°C			
IP Rating	IP65			
Impact Rating	IK08			
LED MacAdam Step (SDCM)	4			
AS2293 Classification	C0=D63 C90=D40			
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3			
Compliance Marking (RCM)				



www.clevertronics.com.au www.clevertronics.co.nz

Version: 26-Mar-21 Template: ARGOPLUS SCO EM File Name: ARGOPLUS-1200-LP-HV_AUB02820640001



ARGOPLUS-1200-LP-HV

CLEVERTRONICS Argonaut Plus 1200mm Weatherproof Emergency Batten, LP, Switchable Colour & Output, Zoneworks Hive



REPLACEMENT PARTS				
COMPONENT	PART NUMBER & DESCRIPTION			
240V Driver	1330092 - LED Driver - 40w Stallion, SP, 650mA, with feet			
240V LED Strip	8002752 - PCA:LED Strip ARGOPLUS-1200,8P16S,3000K/5700K			
Emergency Driver	AUM02870110001 - Lifelight Pro, Control Only, Batten, HV, LP			
Emergency LED Strip	8003110 - PCA: Batten EM Class HT10582-Ax 1S4P			
Battery	1550230 - BATT:LP 3.2V 6400mAh.200mm lead.Brkt.			
Sensor	n/a			

Power Consumption & Lumen Output	Output 2 (650mA)				
	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Off	Lumen Output	
3000К	36.3W	34.0W	0.7W	4145 lm	
4000K (DEFAULT)	35.2W	32.9W	0.7W	4420 lm	
5700K	36.1W	33.8W	0.7W	4322 lm	

Power Consumption & Lumen Output	Output 1 (350mA)				
	Max Charge <i>,</i> Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Off	Lumen Output	
3000К	21.8W	19.5W	0.7W	2432 lm	
4000K	21.4W	19.1W	0.7W	2549 lm	
5700K	21.7W	19.4W	0.7W	2533 lm	

*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order





Version: 26-Mar-21 Template: ARGOPLUS SCO EM File Name: ARGOPLUS-1200-LP-HV_AUB02820640001