



## ARGOPLUS-1500-DD-LPPOD

CLEVERTRONICS Argonaut Plus 1500mm Weatherproof Emergency Batten, LP with POD, Switchable Colour, DALI Driver, Clevertest Plus



### PRODUCT INFORMATION

<b>Product Code</b>	ARGOPLUS-1500-DD-LPPOD
<b>MIC</b>	AUB02320710001
<b>Description</b>	Argonaut Plus 1500mm Weatherproof Emergency Batten, LP with POD, Switchable Colour, DALI Driver, Clevertest Plus
<b>Colour CCT</b>	Switchable 3000K / 4000K (Default) / 5700K
<b>Output Configuration</b>	Fixed Single Output
<b>Battery Configuration</b>	Batteries contained within thermally isolated POD for optimum battery life
<b>Construction</b>	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS304)
<b>Diffuser</b>	Polycarbonate
<b>Mounting</b>	Surface Mount
<b>Operating Mode</b>	SUSTAINED
<b>Testing System</b>	Clevertest Plus Enabled (not activated by default)
<b>Battery</b>	Lithium Iron Phosphate, 3.2V 6400mAh
<b>Charging Method</b>	Intelligent current limited constant voltage
<b>Sensor Capability</b>	n/a
<b>Dimensions LxWxH (mm)</b>	1630x160x105
<b>Weight (kg)</b>	3.9
<b>Driver / Ballast</b>	LED Driver - TCI DC MAXI JOLLY SVM 65 DALI SLIM
<b>Lamp(s)*</b>	LED strip module, 3000K / 5700K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 157,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 95,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr
<b>Supply Voltage</b>	220-240V~ 50Hz
<b>Power Factor</b>	0.93 @ default
<b>Supply Current</b>	226mA +/-20mA
<b>Inrush Current (Max)</b>	17.3A<250µs
<b>Earth Leakage</b>	0.42mA
<b>Total lumen output</b>	6337 lm (141 lm/W) @ default (refer to next page for details)
<b>Power Consumption</b>	44.9W @ default (refer to next page for details)
<b>Operating Temperature</b>	0°C to 40°C
<b>IP Rating</b>	IP65
<b>Impact Rating</b>	IK08
<b>LED MacAdam Step (SDCM)</b>	4
<b>AS2293 Classification</b>	C0=D80 C90=D80
<b>Applicable Standards</b>	AS/NZS3820, CISPR15, AS/NZS2293.3
<b>Compliance Marking (RCM)</b>	



## ARGOPLUS-1500-DD-LPPOD

CLEVERTRONICS Argonaut Plus 1500mm Weatherproof Emergency Batten, LP with POD, Switchable Colour, DALI Driver, Clevertest Plus



### REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1330151	240V Driver
8002753	240V LED Strip
AUM02370050002 CLIFE-PRO-CKIT-NP	EM Driver
8050205	EM LED Strip
1550050	Battery

Power Consumption & Lumen Output	Output (950mA)				
	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
3000K	48.8W	46.5W	n/a	0.4W	5877 lm
4000K (DEFAULT)	47.2W	44.9W	n/a	0.4W	6337 lm
5700K	48.7W	46.4W	n/a	0.4W	6185 lm

\*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order