



## ARGOPRO-1200-DD-LP-HVG

Argonaut Pro 1200mm Weatherproof Emergency Batten, LP, Configurable Output, DALI Driver, Zoneworks XT Hive 2.4GHz



### PRODUCT INFORMATION

Part Number	ARGOPRO-1200-DD-LP-HVG
MIC	AUB02920520001
Description	Argonaut Pro 1200mm Weatherproof Emergency Batten, LP, Configurable Output, DALI Driver, Zoneworks XT Hive 2.4GHz
Colour CCT	4000k
Output Configuration	Configurable Quad Output
Battery Configuration	Integral Battery
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316)
Mounting	Surface Mount
Dimensions L x W x H	1265mm x 160mm x 105mm
Weight	2.9kg
Operating Mode	Sustained
Testing System	Zoneworks XT HIVE (RF)
Battery	Lithium Iron Phosphate, 3.2V 6400mAh
Charging Method	Intelligent current limited constant voltage
Diffuser	Polycarbonate
Driver / Ballast	LED Driver - LCA 50w 350-1050mA, ONEFORALL
Lamp(s)	LED strip module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr
Operating Voltage	220-240V~; 50Hz
Power Factor	0.93 @ default
Supply Current	211mA +/-20mA
Power Consumption	31.9W @ default (refer to next page for details)
Inrush Current (Max)	55.9A<800µs
Earth Leakage	0.585mA
Total Lumen Output	4660 lm (146 lm/W) @ default (refer to next page for details)
Operating Temperature	0°C to 40°C
IP Rating	IP65
Impact Rating	IK08
AS2293 Classification	C0=63, C90=40
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3
Compliance Marking (RCM)	



## ARGOPRO-1200-DD-LP-HVG

Argonaut Pro 1200mm Weatherproof Emergency Batten, LP, Configurable Output, DALI Driver, Zoneworks XT Hive 2.4GHz



### REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1550230	Battery
8003110	LED Strip
8002755	240V LED Strip
AUM02970010001 CLIFE-PRO-CKIT-HVG-NP	Driver Pack
1330056	240V Driver
8003560	HVG Node

Power Consumption & Lumen Output	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
Output 4 (900mA)	45.8W	43.5W	n/a	0.7W	6259 lm
Output 3 (750mA)	40.1W	37.8W	n/a	0.7W	5495 lm
Output 2 (650mA) DEFAULT	34.2W	31.9W	n/a	0.7W	4660 lm
Output 1 (500mA)	27.5W	25.2W	n/a	0.7W	3541 lm

\*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order