



ARGOPRO-1200-DD-LPPOD-HVG

CLEVERTRONICS Argonaut Pro 1200mm Weatherproof Emergency Batten, LP with POD, Configurable Output, DALI Driver, Zoneworks XT Hive 2.4GHz



| PRODUCT INFORMATION | |
|--------------------------|---|
| Product Code | ARGOPRO-1200-DD-LPPOD-HVG |
| MIC | AUB02920290001 |
| Description | Argonaut Pro 1200mm Weatherproof Emergency Batten, LP with POD, Configurable Output, DALI Driver, Zoneworks XT Hive 2.4GHz |
| Colour CCT | 4000K |
| Output Configuration | Configurable Quad Output |
| Battery Configuration | Batteries contained within thermally isolated POD for optimum battery life |
| Construction | Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316) |
| Diffuser | Polycarbonate |
| Mounting | Surface Mount |
| Operating Mode | SUSTAINED |
| Testing System | Zoneworks XTHIVE (RF) |
| Battery | Lithium Iron Phosphate, 3.2V 6400mAh |
| Charging Method | Intelligent current limited constant voltage |
| Sensor Capability | n/a |
| Dimensions LxWxH (mm) | 1330x160x105 |
| Weight (kg) | 3.2 |
| Driver / Ballast | LED Driver - LCA 50w 350-1050mA, ONEFORALL |
| Lamp(s)* | LED strip module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr |
| Supply Voltage | 220-240V~ 50Hz |
| Power Factor | 0.93 @ default |
| Supply Current | 211mA +/-20mA |
| Inrush Current (Max) | 55.9A<800μs |
| Earth Leakage | 0.585mA |
| Total Lumen Output | 4660 lm (146 lm/W) @ default (refer to next page for details) |
| Power Consumption | 31.9W @ default (refer to next page for details) |
| Operating Temperature | 0°C to 40°C |
| IP Rating | IP65 |
| Impact Rating | IK08 |
| LED MacAdam Step (SDCM) | 3 |
| AS2293 Classification | C0=D80 C90=D80 |
| Applicable Standards | AS/NZS3820, CISPR15, AS/NZS2293.3 |
| Compliance Marking (RCM) | |



ARGOPRO-1200-DD-LPPOD-HVG

CLEVERTRONICS Argonaut Pro 1200mm Weatherproof Emergency
Batten, LP with POD, Configurable Output, DALI Driver, Zoneworks
XT Hive 2.4GHz



REPLACEMENT PARTS

| COMPONENT | PART NUMBER & DESCRIPTION |
|------------------|--|
| 240V Driver | 1330056 - LED Driver - LCA 50w 350-1050mA, ONEFORALL |
| 240V LED Strip | 8002755 - PCA: LED Strip ARGOPRO-1200, HT10540-A1, 16P16S, 4000K |
| Emergency Driver | CLIFE-PRO-CKIT-HVG-NP - Lifelight Pro, Control Only, Batten, HVG, LP |
| Node | 8003560 - PCA: V5 2.4GHz RF Node CT10816-A1 Int Ant |
| EM LED Strip | 8050205 - HWSUB: CT10570-A4 - 2 LED WHITE |
| Battery | 1550050 - BATT: LP 3.2V 3200mAh 70mm lead, no BRKT. |
| Sensor | n/a |

| Power Consumption & Lumen Output | Max Charge, Lamp On | Standby Charge, Lamp On | Standby Charge, Lamp Min. 10% (sensor version only) | Standby Charge, Lamp Off | Lumen Output |
|-------------------------------------|------------------------|----------------------------|---|-----------------------------|--------------|
| Output 4 (900mA) | 45.8W | 43.5W | n/a | 0.7W | 6259 lm |
| Output 3 (750mA) | 40.1W | 37.8W | n/a | 0.7W | 5495 lm |
| Output 2 (650mA) DEFAULT | 34.2W | 31.9W | n/a | 0.7W | 4660 lm |
| Output 1 (500mA) | 27.5W | 25.2W | n/a | 0.7W | 3541 lm |

*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order