



ARGOPRO-1200-LPPOD-HVG

CLEVERTRONICS Argonaut Pro 1200mm Weatherproof Emergency Batten, LP with POD, Configurable Output, Zoneworks XT Hive 2.4GHz



PRODUCT INFORMATION

Product Code	ARGOPRO-1200-LPPOD-HVG
MIC	AUB02920230001
Description	Argonaut Pro 1200mm Weatherproof Emergency Batten, LP with POD, Configurable Output, Zoneworks XT Hive 2.4GHz
Colour CCT	4000K
Output Configuration	Configurable Quad Output
Battery Configuration	Batteries contained within thermally isolated POD for optimum battery life
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316)
Diffuser	Polycarbonate
Mounting	Surface Mount
Operating Mode	SUSTAINED
Testing System	Zoneworks XTHIVE (RF)
Battery	Lithium Iron Phosphate, 3.2V 6400mAh
Charging Method	Intelligent current limited constant voltage
Sensor Capability	n/a
Dimensions LxWxH (mm)	1330x160x105
Weight (kg)	3.2
Driver / Ballast	LED Driver - LC 50w 350-1050mA, 20-50V
Lamp(s)*	LED strip module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr
Supply Voltage	220-240V~ 50Hz
Power Factor	0.94 @ default
Supply Current	208mA +/-20mA
Inrush Current (Max)	49.7A<500µs
Earth Leakage	0.51mA
Total Lumen Output	4660 lm (148 lm/W) @ default (refer to next page for details)
Power Consumption	31.4W @ default (refer to next page for details)
Operating Temperature	0°C to 40°C
IP Rating	IP65
Impact Rating	IK08
LED MacAdam Step (SDCM)	3
AS2293 Classification	C0=D80 C90=D80
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3
Compliance Marking (RCM)	



ARGOPRO-1200-LPPOD-HVG

CLEVERTRONICS Argonaut Pro 1200mm Weatherproof Emergency
Batten, LP with POD, Configurable Output, Zoneworks XT Hive
2.4GHz



REPLACEMENT PARTS

COMPONENT	PART NUMBER & DESCRIPTION
240V Driver	1330055 - LED Driver - LC 50w 350-1050mA, 20-50V
240V LED Strip	8002755 - PCA:LED Strip ARGOPRO-1200,HT10540-A1,16P16S,4000K
Emergency Driver	CLIFE-PRO-CKIT-HVG-NP - Lifelight Pro, Control Only, Batten, HVG, LP
Node	8003560 - PCA: V5 2.4GHz RF Node CT10816-A1 Int Ant
EM LED Strip	8050205 - HWSUB: CT10570-A4 - 2 LED WHITE
Battery	1550050 - BATT:LP 3.2V 3200mAh 70mm lead,no BRKT.
Sensor	n/a

Power Consumption & Lumen Output	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
Output 4 (900mA)	45.1W	42.8W	n/a	0.7W	6259 lm
Output 3 (750mA)	39.6W	37.3W	n/a	0.7W	5495 lm
Output 2 (650mA) DEFAULT	33.7W	31.4W	n/a	0.7W	4660 lm
Output 1 (500mA)	26.6W	24.3W	n/a	0.7W	3541 lm

*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order