

ARGOPRO-1500-DD-LP-D2

CLEVERTRONICS Argonaut Pro 1500mm Weatherproof Emergency Batten, LP, DALI Driver, Clevertest Plus



PRODUCT INFORMATION					
Product Code	ARGOPRO-1500-DD-LP-D2				
MIC	AUB02221720001				
Description	Argonaut Pro 1500mm Weatherproof Emergency Batten, LP, DALI Driver, DALI-2				
Colour CCT	4000K				
Output Configuration	Configurable Dual Output				
Battery Configuration	Integral Battery				
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316)				
Diffuser	Polycarbonate				
Mounting	Surface Mount				
Operating Mode	SUSTAINED				
Testing System	DALI-2				
Battery	Lithium Iron Phosphate, 3.2V 6400mAh				
Charging Method	Intelligent current limited constant voltage				
Sensor Capability	n/a				
Dimensions LxWxH (mm)	1565x160x105				
Weight (kg)	3.6				
Driver / Ballast	LED Driver - Tridonic LCA 75W 900–1800mA one4all lp PRE				
Lamp(s)*	LED strip module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr				
Supply Voltage	220-240V~ 50Hz				
Power Factor	0.96 @ default				
Supply Current	279mA +/-20mA				
Inrush Current (Max)	47.9A<800μs				
Earth Leakage	0.566mA				
Total Lumen Output	8498 lm (142.9 lm/W) @ default (refer to next page for details)				
Power Consumption	59.4W@ default (refer to next page for details)				
Operating Temperature	0ºC to 40ºC				
IP Rating	IP65				
Impact Rating	IK08				
LED MacAdam Step (SDCM)	3				
AS2293 Classification	C0=D63 C90=D40				
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3				
Compliance Marking (RCM)					





ARGOPRO-1500-DD-LP-D2

CLEVERTRONICS Argonaut Pro 1500mm Weatherproof Emergency Batten, LP, DALI Driver, Clevertest Plus



REPLACEMENT PARTS		
PART NUMBER	DESCRIPTION	
1330073	240V Driver	
8002756	240V LED Strip	
AUM02270540001 CLIFE-PRO-CKIT-D2-NP	Driver Pack	
8003110	2 x EM LED Strip	
1550230	Battery	
8003062	DALI-2 Node	

Power Consumption & Lumen Output	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
Output 2 (1200mA) DEFAULT	61.7W	59.4W	n/a	0.7W	8498 lm
Output 1 (900mA)	46.7W	44.4W	n/a	0.7W	6358 lm

^{*}The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order

