



ARGOPRO-600-L10POD-HVG

CLEVERTRONICS Argonaut Pro 600mm Weatherproof Emergency Batten, L10 with POD, Zoneworks Hive



PRODUCT INFORMATION

Product Code	ARGOPRO-600-L10POD-HVG
MIC	UKB01820310001
Description	Argonaut Pro 600mm Weatherproof Emergency Batten, L10 with POD, Zoneworks Hive
Colour CCT	4000K
Output Configuration	Fixed Single Output
Battery Configuration	Batteries contained within thermally isolated POD for optimum battery life
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316)
Diffuser	Polycarbonate
Mounting	Surface Mount
Operating Mode	SUSTAINED
Testing System	Zoneworks XT HIVE (RF)
Battery	Lithium Nanophosphate, 3.3V 5000mAh
Charging Method	Intelligent current limited constant voltage
Sensor Capability	n/a
Dimensions LxWxH (mm)	720x160x105
Weight (kg)	2.0
Driver / Ballast	LED Driver - 40W, 500-1050mA, 15-50V
Lamp(s)*	LED strip module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr
Supply Voltage	220-240V~ 50Hz
Power Factor	0.85 @ default
Supply Current	108mA +/-20mA
Inrush Current (Max)	43.9A<500µs
Earth Leakage	0.4mA
Total Lumen Output	2564 lm (135 lm/W) @ default (refer to next page for details)
Power Consumption	19.0W@ default (refer to next page for details)
Operating Temperature	0°C to 40°C
IP Rating	IP65
Impact Rating	IK08
LED MacAdam Step (SDCM)	3
Rated Emergency Duration	180 minutes
Emergency Lumens	333
Compliance Marking	UK CA CE



ARGOPRO-600-L10POD-HVG

CLEVERTRONICS Argonaut Pro 600mm Weatherproof Emergency Batten, L10 with
POD, Zoneworks Hive



PRODUCT INFORMATION

Protection	<ul style="list-style-type: none">Battery overvoltage & overcurrent protectionBattery deep discharge protectionSupply voltage polarity reversal protectionBattery short-circuit protection (charging will resume upon removal of fault)Kit box (enclosure) of lamp controlgear provides protection against accidental contacts with live parts				
Luminaire Classification	X	2	ADF	180	
Conformity	BS IEC 60598-2-22, BS 5266, BS EN IEC 55015, BS EN 61547, BS EN IEC 61000-3-2				

REPLACEMENT PARTS

COMPONENT	PART NUMBER & DESCRIPTION
240V Driver	1330029 - LED Driver - 40W, 500-1050mA, 15-50V
240V LED Strip	8002754 - PCA: LED Strip ARGOPRO-600,HT10515-A1,16P8S, 4000K
Emergency Driver	UKM01870140001 - Lifelight Pro, Control Only, HVG, L10, 415mA
EM LED Strip	8050205 - HWSUB: CT10570-A4 - 2 LED WHITE
Battery	1530050 - BATTERY:L10 3.3V 2.5AH 70mm lead, no Brkt
Sensor	n/a

Power Consumption & Lumen Output	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
Output (700mA)	21.3W	19.0W	n/a	0.7W	2564 lm

*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order