

CIRC-SEN

Circlite, Non-emergency, Switchable Colour, Motion Sensor,

White



| PRODUCT INFORMATION | | | | |
|--------------------------|---|--|--|--|
| Part Number | CIRC-SEN | | | |
| MIC | UKC04610070001 | | | |
| Description | Circlite, Non-emergency, Switchable Colour, Motion Sensor, White | | | |
| Colour CCT | Switchable 3000K / 4000K (Default) / 5700K | | | |
| Switchable output | N/A | | | |
| Material | Base & Diffuser: Polycarbonate | | | |
| Mounting | Ceiling/Wall Surface Mount | | | |
| Sensor Capability | Microwave, High/Low, Master Slave - No | | | |
| Dimensions | Ø350mm x 81mm | | | |
| Weight | 1.43kg | | | |
| Operating Mode | N/A | | | |
| Testing System | N/A | | | |
| Battery | N/A | | | |
| Charging Method | N/A | | | |
| Driver | 30W Stallion, MS-HL2, 500mA output N/A | | | |
| Lamp(s) | LED Panel, 3,000K warm white, 4,000K natural white, 5,700K cool white, Ra>80 L70/B50 Ta 40°C; LM80 Report >54,000hr, Projected 166,000hr L70/B50 Ta 25°C; LM80 Report >54,000hr, Projected 166,000hr L80/B20 Ta 40°C; LM80 Report >54,000hr, Projected 94,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr | | | |
| Operating Voltage | 220-240V~ 50Hz | | | |
| Total Lumen Output | 2257 lm (110.1 lm/W) @default (refer to next page for details) | | | |
| Power Consumption | 21.1W (refer to next page for details) | | | |
| Supply Current | 0.10A +/-20mA | | | |
| Inrush Current (Max) | 6.90 A < 34 μs | | | |
| Earth Leakage | 0.127mA | | | |
| IP Rating | IP20 | | | |
| IK Rating | IK03 | | | |
| LED MacAdam | 5 | | | |
| Operating Temperature | 0°C to 40°C | | | |
| Rated Emergency Duration | N/A | | | |
| Applicable Standards | BS IEC 60598-1, BS EN IEC 55015, BS EN 61547, BS EN IEC 61000-3-2 | | | |
| Compliance Marking | 北 K C C C C C C C C C C C C C | | | |
| Luminaire Classification | N/A | | | |





CIRC-SEN Circlite, Non-emergency, Switchable Colour, Motion Sensor, White

| REPLACEMENT PARTS | | |
|-------------------|------------------|--|
| PART NUMBER | DESCRIPTION | |
| N/A | Battery | |
| 1330103 | 240V Driver | |
| 8051425 | LED Panel | |
| N/A | Emergency Driver | |
| 1190134 | Sensor | |

| Power Consumption & Lumen Output | Output (500mA) | | | |
|-------------------------------------|----------------|------------------|--------------|--|
| | Lamp On | Lamp On, Min 10% | Lumen Output | |
| 3000К | 21.1W | 2.9W | 2141 lm | |
| 4000K | 20.5W | 2.9W | 2257 lm | |
| 5700K | 21.1W | 2.9W | 2192 lm | |

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order

