


CleverEvac Dynamic Red X Exit, Surface Mount, LP, Zoneworks XT Hive 2.4GHz, Running Man Arrow Right, Single Sided



Dynamic LEDs Sequencing Arrow



Illuminated Red X with Side Flashing Red LED's

PRODUCT INFORMATION

Part Number	DYRC-CP-RR-HVG
MIC	AUA02950110001
Description	CleverEvac Dynamic Red X Exit, Surface Mount, LP, Zoneworks XT Hive 2.4GHz, Running Man Arrow Right, Single Sided
Construction	PC/ABS body with PC diffuser
Mounting	Ceiling / Wall mounted single sided
Dimensions L x W x H	367mm x 214mm x 72mm
Weight	2.0kg
Operating Mode	Maintained – Sequencing arrows or illuminated Red X with side flashing Red LED's activated on VF/24V input trigger and capable of being activated in power-on and battery-backed mode. From 1st of April 2022 Dynamic GREEN default set to activate upon mains power fail
Testing System	Zoneworks XTHIVE (RF)
Battery	Lithium Iron Phosphate, 3.2V 6400mAh
Charging Method	Intelligent current limited constant voltage
Diffuser	Pictograph, Single element (Running Man and Arrow Right)
Lamp(s)	LED panel, 100,000 hours
Operating Voltage	240V AC; 50Hz
Power Consumption	1.5 Watts (Standby), 9.0 Watts (Max)
IP Rating	IP20
Operating Temperature	1°C to 40°C
AS2293 Classification	C ₀ =E1.6 C ₉₀ =E1.25 C ₁₈₀ =E1.25
Viewing Distance	24m

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1550232	BATT:LP 3.2V 6400mAh.350mm lead, No Brkt
8002925	PCA: DYxx Driver Board #CT10142-L8
8003560	PCA: V5 2.4GHz RF Node CT10816-A1 Int Ant

Disclaimer: Clevertronics Pty Ltd is a vendor of CleverEVAC products. It is not a fire engineer or designer. It does not purport to recommend its products for use in any particular application or to achieve any particular outcome. Purchasers and users of its products must take their own steps to ensure compliance with statutory requirements, safe practice and suitable application of the products.