



DYRC-UP-RD-HVG

CLP Premium CleverEVAC Dynamic Green and Red X Blade EXIT sign, with Volt Free (VF) & 24V interface for ON/OFF activation of Dynamic Green & Red X Enhancement.



PRODUCT INFORMATION

Part Number	DYRC-UP-RD-HVG				
MIC	UKA02850060002				
Description	CLP Premium CleverEVAC Dynamic Green and Red X Blade EXIT sign, with Volt Free (VF) & 24V interface for ON/OFF activation of Dynamic Green & Red X Enhancement.				
Construction	PC/ABS body with Acrylic diffuser				
Mounting	Recessed, Single-sided				
Dimensions L x W x H	385mm x 67mm x 257mm				
Weight	3.3kg				
Operating Mode	Maintained – Sequencing green LEDs or illuminated Red X with side flashing red LED's activated on VF/24V input trigger and capable of being activated in power-on and battery-backed mode.				
Testing System	Zoneworks HIVE (RF)				
Battery	Lithium Iron Phosphate, 3.2V 3200mAh Lithium Iron Phosphate, 3.2V 6400mAh				
Charging Method	Intelligent current limited constant voltage				
Diffuser	Pictograph, Single element (Running Man with Arrow Down)				
Lamp(s)	LED panel, 100,000 hours				
Operating Voltage	240V AC; 50Hz				
Supply Current	0.09A				
Power Factor	0.427				
Power Consumption	2.0 Watts (Standby), 9.0 Watts (Max)				
Inrush Current (Peak/Duration)	15.6A/134µs				
Earth Leakage	0.366mA				
IP Rating	IP20				
Operating Temperature	0°C to 40°C				
Viewing Distance	30m				
Rated Emergency Duration	180 minutes				
Conformity	BS EN 60598-2-22, BS 5266				
Luminaire Classification	<table border="1"><tr><td>X</td><td>1</td><td>AFG</td><td>180</td></tr></table>	X	1	AFG	180
X	1	AFG	180		
Compliance Marking					
Appliance Class	<input type="checkbox"/> Class II double insulated				

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1553050	Battery
1553250	Battery
UKM02870160002	Emergency Driver
8003330	Node

Disclaimer: Clevertronics Pty Ltd is a vendor of CleverEVAC products. It is not a fire engineer or designer. It does not purport to recommend its products for use in any particular application or to achieve any particular outcome. Purchasers and users of its products must take their own steps to ensure compliance with statutory requirements, safe practice and suitable application of the products.