

## CLEVEREVAC DYNAMIC GREEN & RED X EXIT SIGN



Dynamic LEDs Sequencing Arrow



Illuminated Red X with Side Flashing Red LED's

### PRODUCT INFORMATION

Part Number	DYRL-CP-RL-HV
MIC	AUA01850010001
Description	L10 Lithium Nanophosphate CleverEVAC Dynamic Green and Red X EXIT sign, with Volt Free (VF) & 24V interface for ON/OFF activation of Dynamic Green & Red X Enhancement. <b>From 1<sup>st</sup> of April 2022 Dynamic GREEN default set to activate upon mains power fail</b>
Construction	PC/ABS body with PC diffuser
Mounting	Ceiling / Wall mounted single sided
Dimensions L x W x H	367mm x 214mm x 80mm
Weight	2.0kg
Operating Mode	Maintained – Sequencing arrows or illuminated Red X with side flashing Red LED's activated on VF/24V input trigger and capable of being activated in power-on and battery-backed mode. <b>From 1<sup>st</sup> of April 2022 Dynamic GREEN default set to activate upon mains power fail</b>
Testing System	Zoneworks XTHIVE (RF)
Battery	Lithium Nanophosphate, 3.3V 5000mAh
Charging Method	Intelligent current limited constant voltage
Diffuser	Pictograph, Two elements (Running Man and Arrow Left)
Lamp(s)	LED panel, 100,000 hours
Operating Voltage	240V AC; 50Hz
Power Consumption	1.5 Watts (Standby), 9.0 Watts (Max)
IP Rating	IP20
Operating Temperature	1°C to 40°C
AS2293 Classification	C <sub>0</sub> =E1.6 C <sub>90</sub> =E1.25
Viewing Distance	24m

### REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1530230	BATTERY:L10 3.3V 5AH. 200mm lead.Brkt.
8002925	PCA: DYxx Driver Board #CT10142-L8
8003190	PCA: RF Node CT10678-Ax internal antenna

**Disclaimer:** Clevertronics Pty Ltd is a vendor of CleverEVAC products. It is not a fire engineer or designer. It does not purport to recommend its products for use in any particular application or to achieve any particular outcome. Purchasers and users of its products must take their own steps to ensure compliance with statutory requirements, safe practice and suitable application of the products.