



LP™ Corridor Lens Instructions

Make sure to have the Test switch/status LED run along the longest path in the area being illuminated. If installing multiple products, ensure all products are aligned the same with test switch/status LED along the longest path.



CLIFE-RECSP-CL /
CLIFE-SM-WP-CL

Manufacturer recommended spacing table and mounting heights for $\leq 2.5\text{m}$ corridor width, based on direct illuminance calculations (AS/NZS 2293.1); minimum light level of 0.2lx / 0.5lx avg

Mounting Height [m]	2.1	2.4	2.7	3.0	3.3	3.6	4.0	4.5	5.0	6.0	7.0
Fitting to Wall [m] (B)	12.5	13.9	14.6	15.4	16.4	16.8	17.8	17.8	17.8	18.8	17.4
Fitting to Fitting [m] (A)	33.1	35.9	38.5	40.7	42.7	44.6	46.8	43.1	51.2	54.2	42.8

Note: Spacing for mounting heights higher than 7.0m will depend on number of fittings used as the average of 0.5lx will change. Please discuss your specific requirement with Clevertronics representative.