

ARGOPRO-600-SEN-LP-HVG

Argonaut Pro 600mm Weatherproof Emergency Batten, LP, Motion Sensor, DALI-2 Emergency



PRODUCT INFORMATION				
Product Code	ARGOPRO-600-SEN-LP-HVG			
MIC	AUB0000008101			
Description	Argonaut Pro 600mm Weatherproof Emergency Batten, LP, Motion Sensor, DALI-2 Emergency			
Colour CCT	4000K			
Output Configuration	Fixed Single Output			
Dimensions LxWxH (mm)	655 x 160 x 105			
Weight (kg)	1.7			
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316)			
Mounting	Surface Mount			
Operating Mode	Sustained			
Battery Configuration	Integral Battery			
Testing System	Zoneworks XT Hive (RF) 2.4GHz			
Battery	Lithium Iron Phosphate, 3.2V 6400mAh			
Charging Method	Intelligent Current Limited Constant Voltage			
Sensor Capability	High/Low, Master Slave - No			
Driver / Ballast	LED Driver - 20W Stallion, MS-HL			
Lamp(s)*	LED Strip Module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr			
Total Lumen Output	2564lm (137lm/W) @ default (refer to next page for details)			
LED MacAdam (SDCM)	3			
Supply Voltage	220-240V~ 50Hz			
Power Factor	0.85 @ Default			
Power Consumption	18.7W @ Default (Refer to next page for details)			
Supply Current	107mA +/-20mA			
Inrush Current (Max)	23.23A<800µs			
Earth Leakage	0.4mA			
Operating Temperature	0ºC to 40ºC			
IP Rating	IP65			
Impact Rating	IK08			
AS2293 Classification	C0=D63 C90=D40			
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3			
Compliance Marking (RCM)				





ARGOPRO-600-SEN-LP-HVG Argonaut Pro 600mm Weatherproof Emergency Batten, LP, Motion Sensor, DALI-2 Emergency

REPLACEMENT PARTS			
PART NUMBER	DESCRIPTION		
1550230	Battery		
1330087	240V Driver		
8002754	240V LED Assembly		
AUM02270540001 CLIFE-PRO-CKIT-D2-NP	Emergency Driver		
8003110	Emergency LED Assembly		
8003062	DALI Node		
1190132	Sensor		

Power Consumption & Lumen Output	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
Output (700mA)	21.0W	18.7W	3.2W	0.7W	2564lm

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order

