

ARGOSQ-LP-HVG CLEVERTRONICS CLP ARGONAUT SQUARE WEATHERPROOF LUMINAIRE (ZONEWORKS HIVE)



PRODUCT INFORMATION	1					
Part Number	ARGOSQ-LP-HVG					
MIC	UKS02820140001					
Description	LP Premium Argonaut Square LED Weatherproof Luminaire					
Output Configuration	Configurable Dual Output					
Construction	Die Cast Aluminium Body with Polycarbonate Diffuser					
Mounting	Surface Mount					
Dimensions L x W x H	321mm x 321mm x 97mm					
Weight	3.5kg					
Operating Mode	Sustained					
Testing System	Zoneworks XT HIVE (RF)					
Battery Type & Manufacturer	Lithium Iron Phosphate 3.2V 6400mAh, Clevertronics					
Charging Method	Intelligent Current Limited Constant Voltage					
Diffuser	Polycarbonate					
Lamp(s)	LED module, 4000K cool white, Ra>80 L70/B50 Ta 40ºC; Reported >60,000hr, Projected 205,000hr L80/B20 Ta 40ºC; Reported >60,000hr, Projected 100,000hr L90/B10 Ta 40ºC; Reported >43,000hr, Projected 43,000hr					
Operating Voltage	220-240V AC; 50Hz					
Total Lumen Output	521lm (Emergency) 3242lm (Non-Emergency)					
Power Consumption	24.2W (MAX Charge – Lamp ON), 21.9W (Standby - Lamp ON), 0.7W (Standby – Lamp OFF)					
Rated Emergency Duration	180 minutes					
Operating temperature	0°C to 40°C					
Protection	 Battery overvoltage & overcurrent protection Battery deep discharge protection Supply voltage polarity reversal protection Battery short-circuit protection (charging will resume upon removal of fault) Kit box (enclosure) of lamp controlgear provides protection against accidental contacts with live parts 					
Luminaire Classification	Х	2	ADF	180		
Conformity	BS EN 60598-2-22, BS 5266					

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.





ARGOSQ-LP-HVG CLEVERTRONICS CLP ARGONAUT SQUARE WEATHERPROOF LUMINAIRE (ZONEWORKS HIVE)

REPLACEMENT PARTS				
PART NUMBER	DESCRIPTION			
1550230	Battery			
8050780	LED Panel			
1330094	Mains Driver			
UKM02870240001 ARGOSQ-LP-CKIT-HVG	Emergency Driver Pack			
8003340	Node - HIVE			

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.

Power Consumption & Lumen Output	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Off	Lumen Output
Output 1 (470mA) DEFAULT	24.2W	21.9W	0.7W	3242lm
Output 2 (270mA)	18.7W	16.4W	0.7W	1718lm

