



CLEVERTRONICS CLP ARGONAUT SQUARE WEATHERPROOF LUMINAIRE WITH MOTION SENSOR (HI/LO) (ZONEWORKS HIVE)



PRODUCT INFORMATION						
Part Number	ARGOSQ-SEN-LP-HVG					
MIC	UKS02820150001					
Description	LP Premium Argonaut Square LED Weatherproof Luminaire with Motion Sensor (Hi/Lo					
Output Configuration	Fixed Single Output					
Construction	Die Cast Aluminium Body with Polycarbonate Diffuser					
Mounting	Surface Mount					
Dimensions L x W x H	321mm x 321mm x 97mm					
Weight	3.5kg					
Operating Mode	Sustained					
Testing System	Zoneworks XT HIVE (RF)					
Battery Type & Manufacturer	Lithium Iron Phosphate 3.2V 6400mAh, Clevertronics					
Charging Method	Intelligent Current Limited Constant Voltage					
Diffuser	Polycarbonate					
Lamp(s)	LED module, 4000K cool white, Ra>80 L70/B50 Ta 40°C; Reported >60,000hr, Projected 205,000hr L80/B20 Ta 40°C; Reported >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; Reported >43,000hr, Projected 43,000hr					
Operating Voltage	220-240V AC; 50Hz					
Total Lumen Output	521lm (Emergency) 3242lm (Non-Emergency)					
Power Consumption	24.6W (MAX Charge - Lamp ON), 22.3W (Standby - Lamp ON), 3.8W (Lamp ON Min 10%), 0.7W (Standby - Lamp OFF)					
Rated Emergency Duration	180 minutes					
Operating temperature	0°C to 40°C					
Protection	Battery overvoltage & overcurrent protection Battery deep discharge protection Supply voltage polarity reversal protection Battery short-circuit protection (charging will resume upon removal of fault) Kit box (enclosure) of lamp controlgear provides protection against accidental contacts with live parts					
Luminaire Classification	Х	2	ADF	180		
Conformity	BS EN 60598-2-22, BS 5266					

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.





ARGOSQ-SEN-LP-HVG

CLEVERTRONICS CLP ARGONAUT SQUARE WEATHERPROOF LUMINAIRE
WITH MOTION SENSOR (HI/LO)
(ZONEWORKS HIVE)

REPLACEMENT PARTS		
PART NUMBER	DESCRIPTION	
1550230	Battery	
8050780	LED Panel	
1330095	Mains Driver	
1190133	Microwave Motion Sensor	
UKM02870240001 ARGOSQ-LP-CKIT-HVG	Emergency Driver Pack	
8003340	Node - HIVE	

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.

