

CWFLED-2IPREM-BLK

CLEVERTRONICS LP LED WEATHERPROOF SUPALITE WITH REMOTE LAMPS (IKO8), BLACK



PRODUCT INFORMATION	
Part Number	CWFLED-2IPREM-BLK
MIC	AUE02320060001
Description	LP Premium LED Weatherproof Supalite Flood Unit, Surface Mounted Emergency Light with Dual Remote Lamps (IK08), Black, Enabled with Clevertest Plus
Construction	Polycarbonate
Dimensions L x W x H	Main Enclosure - 380mm x 190mm x 130mm Lamp - 66mm x 80mm x 206mm
Weight	Main Enclosure - 2.6kg Head - 0.36kg
Operating Mode	Non-maintained
Testing System	Clevertest Plus Enabled (Not activated by default)
Battery	Lithium Iron Phosphate, 6.4V 3200mAh
Charging Method	Intelligent Current Limited Constant Voltage
Lamp(s)	2 x LED Heads (adjustable), 600lm per Lamp Head
Operating Voltage	240V AC; 50Hz
Power Consumption	0.7W (Standby), 5.1W (Max)
IP Rating	IP65
IK Rating	IK08
Operating Temperature	-40°C to 40°C (Remote Lamps Only) 0°C to 40°C (Control Gear)
AS2293 Classification	C ₀ =N/A C ₉₀ =N/A
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS2293.3
Compliance Marking (RCM)	&

REPLACEMENT PARTS	
PART NUMBER	DESCRIPTION
1550290	Battery (2 required)
AUM02370210001 CCPLED-18V625C-CKIT	LED Driver Pack
1100551	LED Lamp only (2 required)
1100554	Complete LED Head assembly (incl Lamp and Base) IK08 (2 required)

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.



CWFLED-2IPREM-BLK



CLEVERTRONICS LP LED WEATHERPROOF SUPALITE WITH REMOTE LAMPS (IKO8), BLACK

Inter-connecting cable type and distances

In accordance with AS2293, the maximum distance the control gear and battery can be located from the lamp source is 2m before there is a requirement need to run in fire protected cable. Below is a list indicating the maximum distance and cable size required to mount the CWFLED-2IPREM lamp source 10, 20, 30 & 40m away from the control pack and batteries. Please note that this cable would need to be suitably fire rated. As per the previous page Clevertronics would supply the pack and heads with a short lead and terminal block for the contractor to supply and wire the appropriate 2-wire per lamp head "extension" (4 core in total) cable.

The cable sizes for 10M, 20M, 30M, 40M are as follows:



